

## R-AWPD-20-MS

CFM	Static Pressure in Inches W.G.						
	0.000	0.250	0.500	0.750	1.000	1.250	1.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
700		662 / 0.11	879 / 0.27				
1200	338 / 0.01	779 / 0.15	984 / 0.34	1144 / 0.56	1281 / 0.80	1407 / 1.09	1523 / 1.39
1700	477 / 0.03	882 / 0.20	1102 / 0.43	1261 / 0.68	1393 / 0.95	1511 / 1.25	
2200	617 / 0.06	960 / 0.26	1209 / 0.53	1377 / 0.82	1512 / 1.13	1630 / 1.46	
2700	757 / 0.11	1031 / 0.32	1297 / 0.64	1481 / 0.98	1625 / 1.33		
3200	896 / 0.18	1118 / 0.40	1370 / 0.74	1571 / 1.13			
3700	1036 / 0.28	1221 / 0.52	1441 / 0.86	1647 / 1.29			
4200	1176 / 0.41	1335 / 0.67	1521 / 1.02	1717 / 1.46			
4700	1315 / 0.58	1456 / 0.86	1615 / 1.21				
5200	1455 / 0.78	1582 / 1.09	1720 / 1.45				
5700	1595 / 1.03	1710 / 1.36					
6200	1735 / 1.33						

**Max Sizeable RPM = 1900 RPM. Table shown extended beyond this point for reference only.**

Motor DHP00165 has an rpm range of 300 to 1150.

Motor DHP1/545 has an rpm range of 435 to 1740.

Motor DTP0016 has an rpm range of 300 to 1150.

Motor DTP0016-50 has an rpm range of 300 to 958.

Motor DTP1/54 has an rpm range of 437 to 1750.

Motor DTP1/54-50HZ has an rpm range of 357 to 1426.

Motor EP00165 has an rpm range of 300 to 1150.

Motor EP1/545 has an rpm range of 432 to 1730.

Motor GP0016 has an rpm range of 300 to 1150.

Motor GP0016-50 has an rpm range of 300 to 958.

Motor GP1/54 has an rpm range of 450 to 1800.

Motor GP1/54-50 has an rpm range of 360 to 1440.