

RARTU2-E.152-11

CFM	Static Pressure in Inches W.G.									
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250
RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1000		1493 / 0.27	1650 / 0.39	1779 / 0.51	1898 / 0.62	2008 / 0.74	2110 / 0.85	2208 / 0.97	2304 / 1.10	2398 / 1.23
1250	1625 / 0.34	1783 / 0.46	1923 / 0.60	2046 / 0.75	2155 / 0.89	2256 / 1.03	2350 / 1.18			
1500	1951 / 0.58	2083 / 0.72	2209 / 0.88	2322 / 1.06						
1750	2276 / 0.92	2387 / 1.07								

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

Motor .5018OT3E56-S48PP has an rpm range of 1400 to 1730.

Motor .7518OT3E56-S48PP has an rpm range of 1400 to 1735.

Motor .7518OT3E56-S48PP-50Hz has an rpm range of 1400 to 1410.

Motor 00318OT3E56Z-48PP has an rpm range of 1400 to 1730.

Motor DHP00145 has an rpm range of 1400 to 1750.

Motor DHP00245 has an rpm range of 1400 to 1745.

Motor DHP1/545 has an rpm range of 1400 to 1740.

Motor DTP0014 has an rpm range of 1400 to 1750.

Motor DTP0014-50HZ has an rpm range of 1400 to 1429.

Motor DTP0022 has an rpm range of 1400 to 2400.

Motor DTP0024 has an rpm range of 1400 to 1740.

Motor DTP0024-50HZ has an rpm range of 1400 to 1415.

Motor DTP0032 has an rpm range of 1400 to 2400.

Motor DTP1/54 has an rpm range of 1400 to 1750.

Motor DTP1/54-50HZ has an rpm range of 1400 to 1426.

Motor EP00145 has an rpm range of 1400 to 1745.

Motor EP00245 has an rpm range of 1400 to 1800.

Motor EP1/545 has an rpm range of 1400 to 1730.

Motor GP0014 has an rpm range of 1400 to 1800.

Motor GP0014-50 has an rpm range of 1400 to 1440.

Motor GP0024 has an rpm range of 1400 to 1800.

Motor GP0024-50 has an rpm range of 1400 to 1440.

Motor GP1/54 has an rpm range of 1400 to 1800.

Motor GP1/54-50 has an rpm range of 1400 to 1440.