

RARTU2-E.152-18

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1000			1152 / 0.32	1381 / 0.52	1577 / 0.73	1751 / 0.95	1908 / 1.19	2053 / 1.44	2188 / 1.70
1250		948 / 0.19	1197 / 0.39	1416 / 0.61	1607 / 0.84	1778 / 1.09	1935 / 1.36	2080 / 1.63	2212 / 1.91
1500		1040 / 0.25	1258 / 0.46	1461 / 0.70	1643 / 0.96	1812 / 1.24	1963 / 1.52	2107 / 1.83	2242 / 2.14
1750	935 / 0.13	1142 / 0.32	1335 / 0.54	1518 / 0.80	1689 / 1.08	1850 / 1.38	2000 / 1.70	2139 / 2.03	2270 / 2.36
2000	1068 / 0.20	1252 / 0.40	1423 / 0.65	1590 / 0.92	1748 / 1.22	1899 / 1.55	2041 / 1.88	2176 / 2.23	2304 / 2.59
2250	1201 / 0.28	1368 / 0.51	1522 / 0.77	1672 / 1.06	1817 / 1.38	1958 / 1.72	2093 / 2.08	2223 / 2.45	2344 / 2.83
2500	1335 / 0.39	1485 / 0.63	1627 / 0.91	1763 / 1.22	1897 / 1.56	2028 / 1.91	2153 / 2.29	2277 / 2.69	2395 / 3.09
2750	1469 / 0.51	1606 / 0.78	1736 / 1.08	1862 / 1.41	1984 / 1.76	2106 / 2.13	2223 / 2.52	2338 / 2.93	2453 / 3.37
3000	1603 / 0.67	1730 / 0.96	1850 / 1.28	1966 / 1.62	2079 / 1.99	2191 / 2.38	2302 / 2.79	2412 / 3.22	2517 / 3.66

Max Sizeable RPM = 2700 RPM. Table shown extended beyond this point for reference only.

Motor 162778/A01-ECM-50-240-18 has an rpm range of 900 to 2700.

Motor 162778/A01-ECM-60-240-18 has an rpm range of 900 to 2700.

Motor 162779/A01-ECM-50-480-18 has an rpm range of 900 to 2700.

Motor 162779/A01-ECM-60-480-18 has an rpm range of 900 to 2700.