

RARTU2-E.302-13

CFM	Static Pressure in Inches W.G.											
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1500		1302 / 0.39	1425 / 0.53	1535 / 0.68	1643 / 0.84	1748 / 1.01	1852 / 1.19	1956 / 1.40	2058 / 1.64	2161 / 1.91	2266 / 2.22	2370 / 2.57
1750	1344 / 0.40	1478 / 0.56	1588 / 0.73	1689 / 0.90	1784 / 1.07	1876 / 1.24	1966 / 1.43	2056 / 1.64	2147 / 1.86	2235 / 2.10	2324 / 2.36	

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor DHP00145 has an rpm range of 1200 to 1750.
- Motor DHP00245 has an rpm range of 1200 to 1745.
- Motor DHP1/545 has an rpm range of 1200 to 1740.
- Motor DTP0014 has an rpm range of 1200 to 1750.
- Motor DTP0014-50HZ has an rpm range of 1200 to 1429.
- Motor DTP0022 has an rpm range of 1200 to 2400.
- Motor DTP0024 has an rpm range of 1200 to 1740.
- Motor DTP0024-50HZ has an rpm range of 1200 to 1415.
- Motor DTP0032 has an rpm range of 1200 to 2400.
- Motor DTP1/54 has an rpm range of 1200 to 1750.
- Motor DTP1/54-50HZ has an rpm range of 1200 to 1426.
- Motor EP00145 has an rpm range of 1200 to 1745.
- Motor EP00245 has an rpm range of 1200 to 1800.
- Motor EP1/545 has an rpm range of 1200 to 1730.
- Motor GP0014 has an rpm range of 1200 to 1800.
- Motor GP0014-50 has an rpm range of 1200 to 1440.
- Motor GP0024 has an rpm range of 1200 to 1800.
- Motor GP0024-50 has an rpm range of 1200 to 1440.
- Motor GP1/54 has an rpm range of 1200 to 1800.
- Motor GP1/54-50 has an rpm range of 1200 to 1440.