

RARTU2-E.452-13

CFM	Static Pressure in Inches W.G.									
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250
RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2000	1535 / 0.60	1657 / 0.78	1757 / 0.97	1850 / 1.16	1936 / 1.35	2020 / 1.55	2103 / 1.75	2181 / 1.96	2260 / 2.17	2339 / 2.41
2250	1727 / 0.85	1838 / 1.06	1931 / 1.27	2016 / 1.48	2097 / 1.69	2174 / 1.91	2250 / 2.13	2322 / 2.35	2394 / 2.58	
2500	1919 / 1.17	2021 / 1.39	2108 / 1.63	2187 / 1.86	2262 / 2.10	2334 / 2.34				
2750	2111 / 1.55	2204 / 1.80	2286 / 2.06	2363 / 2.32						

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

Motor DHP00145 has an rpm range of 1200 to 1750.

Motor DHP00245 has an rpm range of 1200 to 1745.

Motor DHP1/545 has an rpm range of 1200 to 1740.

Motor DTP0014 has an rpm range of 1200 to 1750.

Motor DTP0014-50HZ has an rpm range of 1200 to 1429.

Motor DTP0022 has an rpm range of 1200 to 2400.

Motor DTP0024 has an rpm range of 1200 to 1740.

Motor DTP0024-50HZ has an rpm range of 1200 to 1415.

Motor DTP0032 has an rpm range of 1200 to 2400.

Motor DTP1/54 has an rpm range of 1200 to 1750.

Motor DTP1/54-50HZ has an rpm range of 1200 to 1426.

Motor EP00145 has an rpm range of 1200 to 1745.

Motor EP00245 has an rpm range of 1200 to 1800.

Motor EP1/545 has an rpm range of 1200 to 1730.

Motor GP0014 has an rpm range of 1200 to 1800.

Motor GP0014-50 has an rpm range of 1200 to 1440.

Motor GP0024 has an rpm range of 1200 to 1800.

Motor GP0024-50 has an rpm range of 1200 to 1440.

Motor GP1/54 has an rpm range of 1200 to 1800.

Motor GP1/54-50 has an rpm range of 1200 to 1440.