

RARTU2-I.200-11

CFM	Static Pressure in Inches W.G.			
	0.000	0.250	0.500	0.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1500	1963 / 0.59	2095 / 0.73	2219 / 0.90	2333 / 1.07
1550	2029 / 0.66	2156 / 0.79	2276 / 0.96	2388 / 1.15
1600	2094 / 0.72	2219 / 0.87	2336 / 1.04	
1650	2160 / 0.79	2279 / 0.94	2395 / 1.11	
1700	2225 / 0.87	2342 / 1.01		
1750	2291 / 0.94			

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

Motor .5018OT3E56-S48PP has an rpm range of 900 to 1730.

Motor .5018OT3E56-S48PP-50HZ has an rpm range of 900 to 1400.

Motor .7518OT3E56-S48PP has an rpm range of 900 to 1735.

Motor .7518OT3E56-S48PP-50Hz has an rpm range of 900 to 1410.

Motor 00318OT3E56Z-48PP has an rpm range of 900 to 1730.

Motor DHP00145 has an rpm range of 900 to 1750.

Motor DHP00245 has an rpm range of 900 to 1745.

Motor DHP1/545 has an rpm range of 900 to 1740.

Motor DTP0014 has an rpm range of 900 to 1750.

Motor DTP0014-50HZ has an rpm range of 900 to 1429.

Motor DTP0016 has an rpm range of 900 to 1150.

Motor DTP0022 has an rpm range of 900 to 2400.

Motor DTP0024 has an rpm range of 900 to 1740.

Motor DTP0024-50HZ has an rpm range of 900 to 1415.

Motor DTP0032 has an rpm range of 900 to 2400.

Motor DTP1/54 has an rpm range of 900 to 1750.

Motor DTP1/54-50HZ has an rpm range of 900 to 1426.

Motor EP00145 has an rpm range of 900 to 1745.

Motor EP00245 has an rpm range of 900 to 1800.

Motor EP1/545 has an rpm range of 900 to 1730.

Motor GP0014 has an rpm range of 900 to 1800.

Motor GP0014-50 has an rpm range of 900 to 1440.

Motor GP0024 has an rpm range of 900 to 1800.

Motor GP0024-50 has an rpm range of 900 to 1440.

Motor GP1/54 has an rpm range of 900 to 1800.

Motor GP1/54-50 has an rpm range of 900 to 1440.